

# TX-5011-03-3

## Shock sensor 868 MHz Gen2, brown

### Product overview

---

The shock sensor is designed to detect the vibrations made by an intruder trying to break a window or door. The sensor has an internal reed allowing to supervise a door or window using the door magnet that is included.

Sensitivity and pulse count options can be set using DIP switches. A jumper allows to select which reed is in use (left or right or none). In walk-test mode, the blue LED on the front cover will light up when the sensor is in alarm state.



### Details

---

- Learn-Mode technology
- Supervised transmissions
- LED indicating sensor status
- Detects opening of door or window
- Magnet included
- Gross attack and pulse count detection modes
- Compatible with Interlogix 868 MHz Gen2 receivers

# TX-5011-03-3

## Shock sensor 868 MHz Gen2, brown

### Technical specifications

---

#### General

Product type	Magnetic contact, Shock with analyser
--------------	---------------------------------------

---

#### Wired / wireless

Wired-wireless	Wireless
----------------	----------

---

Wireless frequency	868 MHz AM
--------------------	------------

---

#### Electrical

Current consumption	10 $\mu$ A (typical standby)
---------------------	------------------------------

---

Batteries	1 x 3 V Lithium
-----------	-----------------

---

Battery lifetime	3 to 5 years
------------------	--------------

---

#### Physical

Physical dimensions	114 x 32 x 32 mm
---------------------	------------------

---

Colour	Brown
--------	-------

---



As a company of innovation, Carrier Fire & Security reserves the right to change product specifications without notice. For the latest product specifications, visit [firesecurityproducts.com](https://firesecurityproducts.com) online or contact your sales representative.

Last updated on 5 May 2023 - 9:33